
		Тур				Anleitu	ng-Nr.	1 Г			Т	Тур			Anleitung-Nr.			Тур		Anleitung-Nr.			Т	Тур			Anleitung-Nr.		
	VT	4	CDS C		- 16	2				VT	20	CDS	-	16	2		СТ	193	B - 6	4		NT	150S	BT	-	10	3		
	VT	4	CDL C		- 16	2				VT	20	CDL CDS	-	16	2		NT	50T	CDS - 10	2		NT	150S	BT	-	16	3		
	VT	10	CDS S		- 16	2				VT	20		-	25	2		NT	50T	CDL - 10	2		NT	150L	CD	-	6	3		
	VT	10	CDL S		- 16	2				VT	20	CDL		25 10 10	2		NT	50T	CDS - 16	2		NT	150L	CD	-	10	3		
	VT	20	CDL S		- 10	2				VT	20	CDH	-				NT	50T	CDL - 16	2		NT	150L	CD	-	16	3		
	VT	20	CDS C		- 10	2				VT	20	B			3		NT	50T	CDS - 25	2		NT	150L	B	_	6	3		
	VT	20	CDL C		- 10	2				VT	20	B	_	16	3		NT	50T	CDL - 25	2		NT	150L	B	-	10	3		
	VT	20	CDS C		- 16	2				VT	20	B	_	25	1		NT	50M	CDS - 10	2 2 2		NT	150L	B	_	16	3		
	VT	20	CDU C		- 16	2				VT	40	CDS	-	10	2		NT	50M	CDS - 10 CDL - 10			NT	150L	B	-	25	3		
	VT	20			- 10			4		VT	-	CDS		10	2					2					-		3		
			BC			1	_			40		-				NT	50M				NT	150L	BT	-	10	-			
	VT	20	BC	-	- 16	1				VT	40	CDS	-	16	2	i -	NT	50M	CDL - 16	2		NT	150L	BT	-	16	3		
	VT	20	BC	-	- 25	1				VT	40	CDL	-	16	2		NT	50M	CDS - 25	2		NT	150X	В	-	10	3		
	VT	40	CDL S		- 10	2				VT	40	CDS	-	25	2		NT	50M	CDL - 25	2		NT	150X	В	-	16	3		
	VT	40	CDS C		- 6	2				VT	40	CDL		25	2		NT	50X	CDS - 10	2		NT	150X	В	-	25	3		
	VT	40	CDL C		- 6	2				VT	40	CDH	-	10	2		NT	50X	CDL - 10	2		NT	250S	CD	-	6	2		
e	VT	40	CDS C		- 16	2			_ /	1		VT	40	CDM	-	10	2		NT	50X	CDS - 16	2		NT	250S	CD	-	10	2
tel	VT	40	CDL C	-	- 16	2				VT	40	В	-	10	3		NT	50X	CDL - 16	2		NT	250S	В	-	6	5		
Food-Gestelle	VT	40	BC	-	- 6	1				VT	40	В	-	16	3		NT	50X	CDS - 25	2	Industrie-Gestelle	NT	250S	В	-	7	5		
4	VT	40	BC	-	- 16	1				VT	40	В	-	25	3		NT	50X	CDL - 25	2		NT	250S	В	-	10	5		
ŏ	VT	40	BC		- 25	1			đ	Ν	40	CDL	-	10	2	æ	NT	100T	CDL - 6	3		NT	250S	В	-	16	5		
щ	VT	80	BC		- 6	1			elle	Ν	40	CDL	-	16	2	Industrie-Gestelle	NT	100T	CDL - 10	3		NT	250S	В	-	25	5		
	VT	80	BC	-	- 16	1			st	N N VT VT	40	В	-	10	3		NT	100T	CDL - 16	3		NT	250M	В	-	10	5		
	VT	80	BC		- 25	1			Ğ		40	В	-	16	3		NT	100T	B - 10	3		NT	250M	В	-	16	5		
	FA	159	BC		- 6	1			ė		80	CDL	-	6	2		NT	100T	B - 16	3		NT	250M	В	-	25	5		
	FA	161	BC		- 6	1			sti		80	CDL	-	10	2		NT	100T	B - 25	3		NT	250L	В	-	6	5		
	NT	50T	CDL S		- 16	2			qu	VT	80	CDL	-	16	2		NT	100T	BT - 10	3		NT	250L	В	-	7	5		
	NT	50M	CDL S		- 16	2			드	VT	80	В	-	6	3		NT	100T	BT - 16	3		NT	250L	В	-	10	5		
	NT	50X	CDL S		- 16	2				VT	80	В	-	10	3		NT	100M	CDL - 10	3		NT	250L	В	-	16	5		
	NT	100M	CDL C		- 16	2	3			VT	80	В	-	16	3		NT	100M	CDL - 16	3		NT	250L	В	-	25	5		
	NT	100M	BC		- 16	1	3			VT	80	B	-	25	3		NT	100M	B - 10	3		NT	350S	В	-	6	4		
	NT	100M	BC		- 25	1	3			VT	130	B	-	10	4		NT	100M	B - 16	3		NT	350S	B	-	10	4		
	NT	100X	CDL C		- 10	2	3			VT	130	B	_	16	4		NT	100M	B - 25	3		NT	350S	B	-	16	4		
	NT	100X	BC		- 10	1	3			VT	1306	B	-	10	4		NT	100M	CDL - 10	3		NT	350S	B		25	4		
1	NT	100X	BC		- 25	1	3			VT	1306	B		16	4		NT	100X	CDL - 16	3	4	NT	350M	B		6	4		
	NT	150L	BC	+	- 23	5	0			VT	1300	B	Ē	10	4		NT	100X	B - 10	3		NT	350M	B		10	4		
	NT	150L	BC		- 25	5				VT	180	B		10	4		NT	100X	B - 10	3		NT	350M	B	-	16	4		
					- 25 - 10	5 5						B	-	-	-					-	-				-	-	4		
	NT	250L	BC		- 10	Э				VT	180			16	4		NT	100X	B - 25	3		NT	350M	B	-	25	4		
		Optional								VT	250	B	-	6	4		NT	100T	CFL - 16	3	_	NT	350L	B	-	6			
						0		1		VT	250	B	-	10	4	,	NT	100M	CFL - 16	3		NT	350L	B	-	10	4		
Industrie-Gestelle	VT	4	CD		- 16	2				VT	2508	В	-	6	4		NT	100X	CFL - 16	3		NT	350L	В	-	16	4		
	VT	10	CDS	-	- 16	2		- I		VT	2508	В	-	10	4		NT	150S	CD - 6	3		NT	350L	В	-	25	4		
	VT	10	CDL		- 16	2				FA	159	В	-	6	3		NT	150S	CD - 10	3		NF	350	В	-	6	4		
Ģ	VT	10	CDS	-	- 25	2				FA	161	В	-	6	1		NT	150S	CD - 16	3		NF	350	В	-	10	4		
rie	VT	10	CDL		- 25	2				FA	184	CDL	-	6	2		NT	150S	B - 6	3		NT	500T	В	-	10	5		
lst	VT	10	CDH		- 10	2				FA	184	В	-	6	3		NT	150S	B - 10	3		NT	500M	В	-	10	5		
Jpr	VT	20	CDS		- 10	2				FA	192	В	-	6	4		NT	150S	B - 16	3		NT	500X	В	-	10	5		
-	VT	20	CDL	-	- 10	2				FA	192	В	-	8	4		NT	150S	B - 25	3									




Danger to life if the load slips! Always transport the PHE horizontally. Never transport the PHE

using the tensioning bolts.



Danger to life if incorrect slinging equipment is used! Never use steel hawsers or chains. Use only undamaged round slings.

ATTENTION




Damage to connection nozzles!


Never attach slinging equipment to the connection nozzles.

Damage to the heat exchanger plates!


Never transport the PHE using a lift-truck. Always transport the PHE suspended.

Setting up the PHE






- → Use two undamaged round slings of sufficient strength.
- 1. Place the round slings around both top pairs of tensioning nuts of the PHE **[a]** and attach these to the crane hook.
- 2. Tilt the PHE through its centre of gravity [**b**] using lifting gear.
- 3. Lower the PHE slowly to the floor [**c**] and set down in the correct position.



 Attach a round sling to the fixed plate around the **top outer pairs of tensioning nuts** [d] – where the tensioning nuts project insufficiently, the round sling must be placed completely around the base plate.





- 2. Attach another round sling to the removable plate above the **beam** and around the **top outer pairs of tensioning nuts [e]**.
 - ► **Please note:** When two round slings are used, these must be of different lengths!

GEA Heat Exchangers

GEA Ecoflex GmbH

Karl-Schiller-Straße 1-3 · 31157 Sarstedt · Germany Phone +49 5066 601-0 · Fax +49 5066 601-104 info@gea-ecoflex.com · www.gea-phe.com


Lifting

С


3. Lift the PHE slowly, until the round slings are equally tensioned and the PHE is suspended almost horizontally.

Lowering

4. Lower the PHE slowly to prevent any impact when it is set down.




PHE horizontally. **Never** transport the PHE using the tensioning bolts.



Danger to life if incorrect slinging equipment is used! **Never** use steel hawsers or chains. Use only undamaged round slings.

ATTENTION




Damage to connection nozzles!


Never attach slinging equipment to the connection nozzles.

Damage to the heat exchanger plates!

Never transport the PHE using a lift-truck. Always transport the PHE suspended.


Setting up the PHE





- → Use two undamaged round slings of sufficient strength.
- 1. Place the round slings around both top pairs of tensioning nuts of the PHE [a] and attach these to the crane hook.
- 2. Tilt the PHE through its centre of gravity **[b**] using lifting gear.
- 3. Lower the PHE slowly to the floor [c] and set down in the correct position.

Suspended transport of the PHE



Attaching the round slings

1. Attach a round sling of sufficient length or two round slings of equal length around the **top outer pairs** of tensioning nuts [d] on both sides of the PHE.

Lifting

С

2. Lift the PHE slowly, until the round slings are equally tensioned and the PHE is suspended almost horizontally.

Lowering

3. Lower the PHE slowly to prevent any impact when it is set down.



GEA Heat Exchangers


GEA Ecoflex GmbH

Karl-Schiller-Straße 1-3 · 31157 Sarstedt · Germany Phone +49 5066 601-0 · Fax +49 5066 601-104 info@gea-ecoflex.com · www.gea-phe.com






Danger to life if the load slips! Always transport the PHE horizontally. **Never** transport the PHE using the tensioning bolts.



Danger to life if incorrect slinging equipment is used! Never use steel hawsers or chains. Use only undamaged round slings.

ATTENTION




Damage to connection nozzles!


Never attach slinging equipment to the connection nozzles.

Damage to the heat exchanger plates!

Never transport the PHE using a lift-truck. Always transport the PHE suspended.


Setting up the PHE






- → Use two undamaged round slings of sufficient strength.
- Place the round slings around both top pairs of tensioning nuts of the PHE [a] and attach these to the crane hook.
- 2. Tilt the PHE through its centre of gravity [**b**] using lifting gear.
- 3. Lower the PHE slowly to the floor [**c**] and set down in the correct position.

Suspended transport of the PHE



1. Attach a round sling to both **shackle holes** in the fixed plate **[d]** with shackles.



2. Attach another round sling above the **beam** and around the **top outer pairs of tensioning nuts** [**e**] on the removable plate.

► **Please note:** When two round slings are used, these must be of different lengths!

GEA Heat Exchangers

GEA Ecoflex GmbH

Karl-Schiller-Straße 1-3 · 31157 Sarstedt · Germany Phone +49 5066 601-0 · Fax +49 5066 601-104 info@gea-ecoflex.com · www.gea-phe.com

Lifting

3. Lift the PHE slowly, until the round slings are equally tensioned and the PHE is suspended almost horizontally.


Absenken

4. Lower the PHE slowly to prevent any impact when it is set down.

DANGER


Danger to life if the load slips! Always transport the PHE horizontally.

Never transport the PHE using the tensioning bolts.



Danger to life if incorrect slinging equipment is used! Never use steel hawsers or chains when setting up the PHE. Use only undamaged round slings.

ATTENTION




Damage to connection nozzles!


Never attach slinging equipment to the connection nozzles.

Damage to the heat exchanger plates!

Never transport the PHE using a lift-truck. Always transport the PHE suspended.


Setting up the PHE





- ➔ Use two undamaged round slings of sufficient strength.
- Place the round slings around both top pairs of tensioning nuts of the PHE [a] and attach these to the crane hook.
- 2. Tilt the PHE through its centre of gravity [**b**] using lifting gear.
- 3. Lower the PHE slowly to the floor [**c**] and set down in the correct position.

Suspended transport of the PHE



Attaching the sling gears

 Attach a round sling to each transport lug [d], using shackles. (Chains and steel hawsers are allowed only if these have no direct contact with the PHE. Otherwise the PHE may be damaged.)

Lifting

С

2. Lift the PHE slowly, until the round slings are equally tensioned and the PHE is suspended almost horizontally.

Lowering

3. Lower the PHE slowly to prevent any impact when it is set down.



GEA Heat Exchangers


GEA Ecoflex GmbH

Karl-Schiller-Straße 1-3 · 31157 Sarstedt · Germany Phone +49 5066 601-0 · Fax +49 5066 601-104 info@gea-ecoflex.com · www.gea-phe.com




Danger to life if the load slips! Always transport the PHE horizontally. Never transport the PHE

using the tensioning bolts.



Danger to life if incorrect slinging equipment is used! Never use steel hawsers or chains when setting up the PHE. Use only undamaged round slings.




Damage to connection nozzles!


Never attach slinging equipment to the connection nozzles.

Damage to the heat exchanger plates!

Never transport the PHE using a lift-truck. Always transport the PHE suspended.


Setting up the PHE





- → Use two undamaged round slings of sufficient strength.
- Place the round slings around both top pairs of tensioning nuts of the PHE [a] and attach these to the crane hook.
- 2. Tilt the PHE through its centre of gravity **[b**] using lifting gear.
- 3. Lower the PHE slowly to the floor [**c**] and set down in the correct position.

Suspended transport of the PHE



Attaching the round slings

- Attach a round sling to the **hole** in the plate that is bolted to the fixed plate [d], using a shackle. (Chains and steel hawsers are allowed only if these have no direct contact with the PHE. Otherwise the PHE may be damaged.)
- 2. Attach another round sling to the hole in the plate that is bolted to the strut [e], using a shackle.
 Please note:

When two round slings (chains or steel hawsers) are used, these must be of different lengths!

GEA Heat Exchangers

GEA Ecoflex GmbH

Karl-Schiller-Straße 1-3 · 31157 Sarstedt · Germany Phone +49 5066 601-0 · Fax +49 5066 601-104 info@gea-ecoflex.com · www.gea-phe.com

Lifting

С

3. Lift the PHE slowly, until the round slings are equally tensioned and the PHE is suspended almost horizontally.

Lowering

4. Lower the PHE slowly to prevent any impact when it is set down.

